



Overview

IR remote controller is an accessory which is compatible with Tracer LPLI and LS LPLI series solar charge controller. The function is to set the system voltage, battery type, control parameters, working time and current of LED lamp, etc, and view the working status of system and load test function.



Features

- Setting parameter via IR communication
- One-key parameter sending, one-to-one setting
- Compatible with the road solar controller
- Dot matrix LCD display
- Load test mode, detection system connection timely



Technical Specifications

Item	RC-10
Apply to model	Tracer LPLI series, LS-LPLI series
Battery	2 batteries (size AA)
Power supply voltage	3VDC
Communication distance	≤10m
Self-consumption	20uA
Sending consumption	37mA
Backlight consumption	3mA
LED consumption(flashlight)	11mA
Environment temperature	0~45℃
Enclosure	IP40
Overall dimension	138 × 58 × 21mm
Net weight	75g